



WatchIt+

Wireless IP Camera

Part No.: **TM013**

WatchIt+ is a video security accessory that securely streams video to your smartphone.

Features:

- » Supports Wi-Fi IEEE 802.11 b/g/n
- » Built-in Microphone /Speaker
- » 8 Infrared LEDs for night vision
- » Supports E-PTZ
- » Easy wireless video monitoring
- » Designed for iOS and Android platforms



Specification - Camers:

Image Sensor	1600 x 1200 CMOS
Picture Resolution	320 x 240 px
Lens	» Focal Length: 3 mm » Max Aperture Ratio: F2.0
Filter	850 nm - IR filter
Field of View	Horizontal up to 49.9°
Focusing Range	0.5 m – ∞
Minimum Illumination	» IR Mode: 0 lux; using built-in IR light in darkness up to 8m » Color Mode: 1.0 lux
Illumination LEDs	8x 850 nm IR LED, with Auto / ON / Off. With Always on / Always off / Auto settings controlled by light sensor » IR turns on when illuminance is around to 3 ± 2 lux » IR turns off when illuminance is around to 8 ± 3 lux
Shutter Time	1/5 – 1/16000 Sec
Image Orientation	Standard, Flip



Made in China



* The specifications and pictures are subject to change without notice.
*All trade names referenced are the registered namework of their respective owners.



WatchIt+

Wireless IP Camera

Part No.: **TM013**

Working Frequency	2.4 – 2.4835 GHz
Output Power	<15 dBm

Video:

Codecs	H.264, JPEG for still images
Resolutions	320 x 240 px, 640 x 480 px (Cloud video recording)
Frame Rate	Up to 30 frames/s
Video Features	<ul style="list-style-type: none"> » Adjustable image size and quality » Flip and mirror image

Audio:

Audio In	Built-in Microphone, -38 dB ± 2 dB
Audio Out	Supported
Audio Compression	G.711, PCM

Network / Access Point:

Security	WPA2-PSK (AES, TKIP), WPA-PSK (AES, TKIP), 128/64-bit WEP
Wireless Networking	802.11b/g/n Wireless with WEP/WPA/ WPA2 security
Frequency	2.412 – 2.462 GHz
AP-Client	Support AP-Client
Mac Address Filtering	Support Mac Address Filtering for increased security
DHCP	DHCP Server





WatchIt+

Wireless IP Camera

Part No.: **TM013**

General:

System	Processor: RT5350 Speed: 360MHz DRAM: 64MB Flash: 8MB
Button	RESET Button » Reset System: Press 1 second to reset the system » Factory default: Press and hold 20 seconds to restore the factory default settings
Switch	Setup mode switch: Turn setup mode on / off
Connector	DC Jack
Power	External AC-to-DC switching power adapter Input: 100-249V AC, 50/60Hz Output: 5V DC, 1.0A
LEDs	Setup Mode LED » Solid Green: Setup mode on » Orange: In progress to switch to Setup Mode » No light: Setup mode off Network LED » Solid Orange: Local network ok » Solid Green: Connection to Seedonk server ok » Flashing Orange: No local network yet » Flashing Green: Global internet ok System LED » Solid green: system on
Max. Power Consumption	<4W
Operation Conditions	Temperature: 32°F to 104°F (0°C to 40°C) Humidity: 20-80% RH Non-Condensing
Storage Conditions	Temperature: -4°F to 140°F (-20°C to 60°C) Humidity: 5%-95% RH Non-Condensing



Made in China



* The specifications and pictures are subject to change without notice.
*All trade names referenced are the registered namework of their respective owners.



WatchIt+

Wireless IP Camera

Part No.: **TM013**

Software:

iPhone/iPad App

- » Easy Camera Setup via mobile
- » Direct Viewing of Camera
- » iSecurity+ app



Package Contents:

- » 1x WatchIt+ - Wireless IP Camera
- » 1x Power Adapter
- » 1x Camera Base and Mounting Kit
- » 1x Quick Installation Guide
- » 1x User Manual

Package Informations:

- » Packing Dimension: 157 x 103 x 100 mm
- » Packing Weight: 0.45 Kg
- » Carton Dimension: 545 x 365 x 235 mm
- » Carton Q'ty: 20 pcs
- » Carton Weight: 10.5 Kg



* The specifications and pictures are subject to change without notice.
* All trade names referenced are the registered namework of their respective owners.



Made in China